

10 Input Mixer Amplifier with Equalizer 60W



Mixer Amplifier

DESCRIPTION

The NVS-90170061MA is a 10 input Mixer Amplifier with Equalizer and have rated voltage outputs of 100V, 70V and rated resistance outputs of 4-16Ω. It provide 4 audio source input ports, 6 microphone input ports, a line output port and 4 power amplifier's output terminals. 4 audio source channels can be selected automatically. The loudness of each of the six microphones can be adjusted separately. The total output volume is controlled by a master-volume control. The output can be adjusted using the 7-band equalizers (EQ). The goods offer multiple protection, well-defined functions, and a steady working condition, and can meet the sound amplification and background music needs of a conference site.

FEATURES

- ⦿ 4 audio source channels can be selected automatically
- ⦿ 7-band equalizer and with convenient adjustment function.
- ⦿ Each of the six microphones' volume can be changed independently.
- ⦿ Contains 4 line inputs, 1 line output, 6 microphone inputs
- ⦿ Provide microphone frequency shift function.

Specifications	
Model	NVS-90170061MA
Rated Power	60W
Frequency Response	50Hz - 20kHz (±3dB)
Input Sensitivity	Mic : 2.5mV (±0.5mV) Line : 120mV (±50mV)
Total Harmonic Distortion	<1% (1kHz, 1/3 rated output voltage)
Signal to Noise Ratio	Line≥70dB
7-band equalizer	64Hz: ±12dB (±2dB) 160Hz: ±12dB (±2dB) 400Hz: ±12dB (±2dB) 1kHz: ±12dB (±2dB) 2.5kHz: ±12dB (±2dB) 6.4kHz: ±12dB (±2dB) 15kHz: ±12dB (±2dB)
Protection function	DC, overload, short-circuit

10 Input Mixer Amplifier with Equalizer 60W

Output Voltage Adjust	<3dB (from off-load to full load)
Rated Output Voltage/ Impedance	70V, 100V/ 4-16Ω
Phantom power	DC 24V
Power Supply	AC 220-240V/ 50-60Hz
Power consumption	120W
Weight	10.2Kg
Dimension(L×W×H)	430×368×88mm

ORDERING INFORMATION

Part Number	Description	Standard Quantity
NVS-90170061MA	10 Input Mixer Amplifier with Equalizer 60W	1