

35W Mini Digital Mixer Amplifier with USB & Bluetooth



DESCRIPTION

The NVS-90270031MA is a s 1.5U designed Mini Digital amplifier with USB/FM and Bluetooth. The Speaker output is 70V/100V and 4-16Ω available. It has 3 auxiliary input, Mic1 is 6.3mm jack in front panel and Mic2 is XLR in rear panel and Phantom power available for Mic2. Individual volume control for each Mic and Aux, also provide Bass and Treble control. It also has EMC signal input for emergency situation.

FEATURES

- ⦿ Fashionable design, compact mini size public address amplifier
- ⦿ Speaker output of 100V or 70V & 4 -16 ohms
- ⦿ 2 MIC input(1 6.3mm MIC & 2 XLR MIC),1 EMC input,2 line inputs,1 line output.
- ⦿ LED indicators for power, clip, protect and signal.
- ⦿ Individual volume control for Mic 1-3, line 1-2, Mp3/FM, bass/treble and master volume control
- ⦿ Built in Mp3 player, FM radio & Bluetooth with remote controller
- ⦿ Built in Class-D amplifier module and switching power, with 100V/70V transformer

Specifications

Model	NVS-90270031MA
Rated power	35W
Frequency Response	MIC: 180Hz~10kHz(±3dB) Line: 70Hz~16kHz(±3dB)
Input Sensitivity	MIC: 5mV Line: 350mV
Total Harmonic Distortion	<1% 1kHz
Signal to Noise Ratio	<5mV (4Ω load output terminal)
Tone Adjustment	Bass: 10dB(±2) Treble: 10dB(±2)
Rated Output Voltage/ Impedance	70V/ 100V/ 4-16 Ω
Output Voltage	35W/4Ω, AC 220V
Power Supply	AC~110-220V
Weight	2.55kg
Dimension	247x198x66mm

ORDERING INFORMATION

Part Number	Description	Standard Quantity
NVS-90270031MA	35W Mini Digital Mixer Amplifier with USB & Bluetooth	01