

2 Zones mixer amplifier with remote paging 350W



DESCRIPTION

The NVS-PA0026002CP is a two-zone mixer amplifier equipped with U disc, radio, Bluetooth, zones, and remote paging capabilities. It is a two-zone mixer amplifier equipped with U disc, radio, Bluetooth, zones, and remote paging capabilities. With numerous features, such as configurable input priority, EMC input, Mic input with phantom power, and clear screen status display. The process is very simple and user-friendly. The product can be used broadly and can fulfil user requirements.

FEATURES

- ⦿ Built-in 4 Mic and 2 AUX and USB/FM/Bluetooth
- ⦿ Support 2 remote paging stations
- ⦿ Individual volume control for Mic 1-4 and Line 1-2
- ⦿ Mic 2-4 with phantom power 48V and gain control
- ⦿ Equipped with chime/Siren/Mute inputs with gain control
- ⦿ Priority: EMC/MIC1/Remote Microphone/Short Circuit adjustable
- ⦿ Built-in two zones of 100V output
- ⦿ 70V/100V & 4-16Ω speaker output

Specifications	
Model	NVS-PA0026002CP
Rated Power	350W
Frequency Response	80Hz-16kHz
Input Sensitivity	Mic: 5.0mV(±0.5mV) Line: 775mV(±40mV)
Total Harmonic Distortion	≤1% at 1 kHz
Output	70V/100V& 4-16Ω
Weight	13.6kg
Dimension	420×403×88mm

ORDERING INFORMATION

Part Number	Description	Standard Quantity
NVS-PA0026002CP	2 Zones mixer amplifier with remote paging 350W	01