

120W Mini Digital Mixer Amplifier with USB & Bluetooth

Mixer Amplifier



DESCRIPTION

The NVS-90220121MA is a Mini Digital amplifier with USB/FM and Bluetooth. The Amplifier provides, speaker output 70V/100V and 4-16Ω. 3 Aux input, Min1 is 6.3 mm jack in front panel and Mic2 is XLR in rear panel were available. There is Phantom power available for Mic2. Individual volume control for each Mic and Aux, also provide Bass and Treble control. It also has EMC signal input for the emergency situations.

FEATURES

- ⦿ Built-in Bluetooth, FM, and USB function
- ⦿ 2 MIC inputs, 2 EMC inputs, 2 line inputs, 1 line output
- ⦿ Support 100V/70V constant voltage output, and 4 -16Ω constant resistance output
- ⦿ Can be controlled by the infrared remote controller
- ⦿ With priority function, the priority is EMC/MIC1>AUX1/AUX2/MIC2
- ⦿ With master volume control, individual volume control for MIC & LINE, treble and bass volume control

Specifications

Model	NVS-90220121MA
Rated Power	120W
Frequency Response	Mic: 100Hz~8kHz(±3dB) Line: 80Hz~15kHz(±3dB)
Input Sensitivity	Mic: 7mV±1mV Line: 300mV±10% EMC: 350mV±10%
Total Harmonic Distortion	<1% 1kHz
Signal to Noise Ratio	≤6mV(4Ω load out)
Tone	Treble: 10dB (±2) Bass: 10dB (±2)
Output voltage/Impedance	70V,100V/4-16Ω
Power Supply	~110-240V 50/60Hz
Weight	3Kg
Dimension(L×W×H)	198×247×66mm

ORDERING INFORMATION

Part Number	Description	Standard Quantity
NVS-90220121MA	120W Mini Digital Mixer Amplifier with USB & Bluetooth	01