

60W Mini Digital Mixer Amplifier with USB & Bluetooth



Mixer Amplifier

DESCRIPTION

The NVS-90210061MA is a 1.5U designed Mini Digital amplifier with USB/FM and Bluetooth and have outputs of 100 V, 70 V, and rated resistance outputs of 4-16 Ω. It is a built-in Class-D amplifier module and switching power, with 100V/70V transformer technology. It provide 2 auxiliary input. Microphone1 is 6.3mm jack in front panel and Microphone2 is XLR in rear panel, also phantom power is available for Microphone2. For each microphone and auxiliary, individual volume control is available. It also contain EMC signal input for emergency situation.

FEATURES

- ⦿ Built in Mp3 player, FM radio & Bluetooth with remote controller
- ⦿ 2 microphone input, 2 EMC inputs, 2 line inputs, 1 line output
- ⦿ Individual volume control for Microphone 1-2, line 1-2, Mp3/FM, bass/treble and master volume control
- ⦿ LED indicators for power, clip, protect and signal
- ⦿ Priority: EMC > Microphone1 > Auxiliary1/Auxiliary2/Microphone2
- ⦿ Support both AC110-240V & DC 24V power supply
- ⦿ Fashionable design, compact mini size public address amplifier
- ⦿ Speaker output of 100V or 70V & 4 -16 ohms

Specifications	
Model	NVS-90210061MA
Rated Power	60W
Frequency Response	Mic: 200Hz~10kHz(±3dB) Line: 80Hz~16kHz(±3dB)
Input sensitivity	Mic: 7.5m±1mV Line: 360mV±10%
Total Harmonic Distortion	<1% 1KHz
Signal to Noise Ratio	<5mV (4Ω load output terminal)
Tone	Treble: 10dB(±2) Bass: 10dB(±2)
Power Supply	AC110-240V & DC 24V
Output voltage/Impedance	70V,100V/4-16Ω
Weight	2.6kg
Dimension(D×W×H)	198×247×66mm

ORDERING INFORMATION

Part Number	Description	Standard Quantity
NVS-90210061MA	60W Mini Digital Mixer Amplifier with USB & Bluetooth	01