

# 2 Zones Mixer Amplifier with Remote Paging 250W



## DESCRIPTION

The NVS-PA0025002CP is a two-zone mixer amplifier equipped with U disc, radio, Bluetooth, zones, and remote paging capabilities. A two-zone mixer amplifier equipped with USB disc, radio, Bluetooth, zones, and remote paging capabilities. It is equipped with numerous features such as configurable input priority, EMC input, Mic input with phantom power, and clear screen status display.

## FEATURES

- ⦿ 4 kinds of audio source mode selection: AUX/ BL/ FM/ USB
- ⦿ Segment code LCD screen, more user-friendly choice of function and operation function
- ⦿ 2-channel AUX IN unbalanced Lotus input interface
- ⦿ 3-level custom priority function, priority order is; EMC>MIC1> remote paging
- ⦿ 1-channel EMC alarm signal input
- ⦿ Independent MIC 1 volume controller, adjustable volume size
- ⦿ Digital tone adjustment, bass and treble adjustments are possible regardless of the source mode
- ⦿ Power indicator and signal indicator
- ⦿ Support up to 2 remote paging microphone

Specifications	
Model	NVS-PA0025002CP
Rated Power	250W
Frequency Response	60Hz-16kHz(±3dB)
Input Sensitivity	Mic: ±5mv Line: 300mv±30mv EMC:375mv±30mv
Total Harmonic Distortion	≤1% at 1 kHz
Signal to Noise Ratio	≥75dB
Tone Adjustment	Bass: 100Hz ±10±2dB Treble: 10kHz ±10±2 dB
Phantom power	48V±2V
Power Supply	AC 220-240V/50HZ/60HZ
Power Consumption	500W
Dimension	420×403×88mm

## ORDERING INFORMATION

Part Number	Description	Standard Quantity
NVS-PA0025002CP	2 Zones mixer amplifier with remote paging 250W	01