## NVS-30050001MP



# Wireless Microphone Set (2 hand-held)



## **DESCRIPTION**

The NVS-30050001MP is a Wireless Microphone Set with two hand-held microphones. It adapts infrared matching technology and it is equipped with two output interfaces for remote monitoring.

### **FEATURES**

- Dual channel PLL technology
- Adopt UHF 200 channel with PLL digital lock automatic communication function
- Adopt IR frequency pairing
- Equipped with volume control for each channel
- LCD screen displaying frequency, channel, squelch, level, etc.
- $_{ullet}$  AF output
- Maximum working distance up to 300m


Specifications		
Model		NVS-30050001MP
Working Frequency		632 - 661.25MHz
Modulation Type		FM
Number of Channels		100
Channel Spacing		250kHz
Dynamic Range		82dB
Maximum Deviation		±45kHz
Frequency Response		120Hz~15KHz (±3dB)
Signal to Noise Ratio		>70dB
Composite Distortion		≤1%
Working Distance		300m Max
Working Temperature		-10°C ~ +40°C
Package Dimension		530×335×330mm
Gross Weight		5.2Kg
Receiver	Wireless Connector	ΒΝC/50Ω
	Sensitivity	≤-95dBm
	Operating Power	DC12V, 600mA
	Dimension	2.3kg
	Weight	430×176×44mm

## NVS-30050001MP




## Wireless Microphone Set (2 hand-held)

### **FRONT PANEL**



- 1. Power Switch
- 2. Power Indicator
- 3. IR Frequency Pairing
- 4. Display Screen
- 5. Channel 1 Selection Button and Mode Switching Button
- 6. Channel 2 Selection Button and Mode Switching Button
- 7. Volume Control(+)
- 8. Volume Control(-)
- 9. Frequency UP Button
- 10. Frequency DOWN Button
- 11. Set Button(SET)

### **REAR PANEL**



- 1. Antenna Input Port
- 2. AF Channel 2 Output Port
- 3. AF Mixing Output Microphone Interface
- 4. Mixing Output Amplitude Adjustment Switch
- 5. AF Channel 1 Output Port
- 6. DC IN (DC12V)

### **ORDERING INFORMATION**

Part Number	Description	Standard Quantity
NVS-30050001MP	Wireless Microphone Set (2 hand-held)	01

## **ACCESSORIES INFORMATION**

Description	Standard Quantity
Power Adapter	01
Battery	04
Audio Cable	01
Antenna	04
5x19 Cross Recessed Raised Countersunk Head Screw	04
Packer Washer	04
Handle	02
3x8 Cross Recessed Countersunk Head Screw	06
User Manual	01