

250W Mini Digital Mixer Amplifier with USB & Bluetooth



DESCRIPTION

The NVS-90230251MA is Mini Digital Mixer Amplifier with inbuilt USB/FM and Blue tooth. Both 70V/100V and 4-16 Ω Speaker outputs are available. It has separate volume control for each Mic and Aux input, also have Master Volume, Bass and Treble control.

FEATURES

- Built-in Bluetooth, radio and USB function
- 2 MIC IN, 2 EMC IN, 2 LINE IN, 1 LINE OUT
- Support IR remote control.
- With priority function, priority is EMC/MIC1>AUX1/AUX2/MIC2
- With master volume control, and individual volume control of MIC & LINE, as well as treble and bass volume control
- 70V/100V constant voltage output, 4 Ω ~16 Ω constant resistance output.

Specifications	
Model	NVS-90230251MA
Rated Power	250W
Frequency Response	Mic: 200Hz~10kHz(± 3 dB) Line: 100Hz~16kHz(± 3 dB)
Input Sensitivity	Mic: 10mV $\pm 10\%$ Line: 350mV $\pm 10\%$
Total Harmonic Distortion	<1% 1KHz
Signal to Noise Ratio	<10mV
Tone	Bass: 10dB(± 2) Treble: 10dB(± 2)
Output Voltage/Impedance	70V/100V and 4-16 Ω
Power Supply	AC110-120V / AC220~240V 50/60Hz (Select via the switch)
Weight	3kg
Dimension	250 \times 230 \times 66mm

ORDERING INFORMATION

Part Number	Description	Standard Quantity
NVS-90230251MA	250W Mini Digital Mixer Amplifier with USB & Bluetooth	01